



Knowledge Base > Handsets and Device Provisioning > Handsets > Cisco SPA – Configuring your phone

Cisco SPA – Configuring your phone

Santiago Garcia - 2024-10-24 - Handsets

Cisco SPA – Configuring your phone

Quick Guide to Cisco SPA

While Cisco don't support encryption for remote device configuration connecting the Cisco SPA to our service is straight forward.

Your browser does not support the video tag.

Cisco SPA Web UI

- Retrieve the phones IP address > select the Settings button (highlighted below)
- Network (9) >> Current IP | Copy the IP
- Advanced settings: in browser type `http://<address>/admin/advanced` (eg `192.168.1.168/admin/advanced`) to access admin mode.



Ext tabs

All the main settings required to configure the Cisco SPA's are accessed within the Ext tabs. Complete:

1. General | Line enable Yes / NO (enable to YES)
2. Proxy and Registration
 - Proxy + Outbound Proxy: plus.2talk.com
 - Register: **Yes**
 - Reg Expires: **120**
3. Subscriber information
 - Display Name: can be both a Human name / or phone number
 - Auth ID: full phone number including country (eg 13106351796)
 - User ID: full phone number including country

Small Business SPA504G Configuration Utility

User Login basic | advanced

Voice Call History Personal Directory Attendant Console Status

Info System SIP Provisioning Regional Phone User Attendant Console

Ext 1 Ext 2 Ext 3 Ext 4

General

Line Enable: yes

Call Feature Settings

Blind Attn-Xfer Enable: no
 Message Waiting: yes
 Default Ring: 2
 Conference Bridge URL:
 Mailbox ID:
 Voice Mail Subscribe Interval: 86400
 CFWD Notify Serv: no
 User ID with Domain: no
 Auto Ans Page On Active Call: yes
 Call Park Monitor Enable: no

MOH Server:
 Auth Page: no
 Auth Page Realm:
 Auth Page Password:
 Voice Mail Server:
 State Agent:
 CFWD Notifier:
 Broadcast ACD: no
 Feature Key Sync: no

Proxy and Registration

Proxy: call.sipcity.com.au
 Outbound Proxy: call.sipcity.com.au
 Alternate Proxy:
 Alternate Outbound Proxy:
 Use Outbound Proxy: no
 Register: yes
 Register Expires: 120
 Use DNS SRV: no
 Proxy fallback Invt: 3600
 Dual Registration: no

Use OB Proxy In Dialog: yes
 Make Call Without Reg: no
 Ans Call Without Reg: no
 DNS SRV Auto Prefix: no
 Proxy Redundancy Method: Normal

Subscriber Information

Display Name: 61289707510
 Password: *****
 Auth ID: 61289707510
 User ID: 61289707510
 Use Auth ID: yes
 Reversed Auth Realm:
 SRTP Private Key:
 Resident Online Number:
 SIP URI:

Additional Extensions

If you are not registering any additional lines on the Cisco SPA set Ext2, Ext3, Ext4 to:

- Line Enable: **No**

Time Zones

1. Type IP into browser followed by /admin/advanced (eg 192.168.1.162/admin/advanced)
2. System | Optional Network Configuration | Primary NTP >> time.google.com

Daylight Saving Time rules

1. Type IP into browser followed by /admin/advanced (eg 192.168.1.162/admin/advanced)
2. Regional | Miscellaneous >> Daylight Saving Time
Rule: start=10/30/-7/2:0:0;end=4/1/7/2:0:0; save=1
3. Set time zone rule

Tags

Device

Handsets